

RAMPA Cap Nuts type RF
with flathead and hexagonal socket make visible joints more decorative.
Please note:
Article group 035 (steel) without through bore.

Threads available in UNC.
Sizes not included in our range can be requested.

Maryland Metrics
<http://mdmetric.com>

Brass

XXX = available from stock

Brass Article No.	Head Ø	Shank Ø	Shank Length	Internal Thread	Internal Hex Socket	Kilos per 1000	Brass plain	Brass brown coloured ¹⁾	Brass nickel plated ²⁾
025 613 01.	13	8	10	M 6	SW 5	3,5	XXX	XXX	XXX
025 615 01.	15	9	10	M 6	SW 5	5,3	XXX	XXX	XXX
025 620 01.	20	9	10	M 6	SW 5	7,6	XXX	XXX	XXX
025 621 01.	20	9	15	M 6	SW 5	10,3	XXX	XXX	XXX
025 817 01.	17	10	11,5	M 8	SW 5	7,1	XXX	XXX	XXX
025 820 01.	20	10	10	M 8	SW 5	8,4	XXX	XXX	XXX
025 825 01.	25	14	10	M 8	SW 5	16,0	XXX	XXX	XXX
025 826 01.	25	10	15	M 8	SW 5	10,9	XXX	XXX	XXX
025 827 01.	25	10	20	M 8	SW 5	14,0	XXX	XXX	XXX
025 830 01.	30	14	18	M 8	SW 5	29,0	XXX	XXX	XXX
025 125 01.	25	14	10	M 10	SW 5	15,0	XXX		XXX
025 130 01.	30	14	18	M 10	SW 5	25,0	XXX	XXX	XXX



RAMPA Cap Nuts type RF

↑ Please complete in order
¹⁾ 7 for brass brown coloured
²⁾ 3 for brass nickel plated

Stainless Steel 1.4305

Stainless Steel Article No.	Head Ø	Shank Ø	Shank Length	Internal Thread	Internal Hex Socket	Kilos per 1000	Steel plain	Steel brown coloured ¹⁾	Steel nickel plated ²⁾	Steel zinc plated ³⁾
025 615 03	15	9	10	M 6	SW 5	5,3	XXX			
025 621 03	20	9	15	M 6	SW 5	10,3	XXX			
025 819 03	20	10	15	M 8	SW 5	9,0	XXX			
025 165 03	25	14	18	M 10	SW 6	17,5	XXX			

Steel

Steel Article No.	Head Ø	Shank Ø	Shank Length	Internal Thread	Internal Hex Socket	Kilos per 1000	Steel plain	Steel brown coloured ¹⁾	Steel nickel plated ²⁾	Steel zinc plated ³⁾
035 610 05.	15	9	10	M 6	SW 5	5,0		XXX	XXX	XXX
035 612 84.	15	8	12	M 6	SW 4	5,6	XXX	XXX	XXX	
035 612 04.	15	9	12	M 6	SW 4	5,6	XXX	XXX	XXX	
035 612 85.	15	8	12	M 6	SW 5	5,6	XXX	XXX	XXX	
035 612 05.	15	9	12	M 6	SW 5	5,6	XXX	XXX	XXX	XXX
035 615 84.	15	8	15	M 6	SW 4	6,5	XXX	XXX	XXX	
035 615 04.	15	9	15	M 6	SW 4	6,5	XXX	XXX	XXX	
035 615 05.	15	9	15	M 6	SW 5	6,5	XXX	XXX	XXX	
035 618 04.	15	9	18	M 6	SW 4	8,0	XXX	XXX	XXX	
035 618 05.	15	9	18	M 6	SW 5	8,0	XXX	XXX	XXX	
035 613 05.	17	9	12	M 6	SW 5	6,3		XXX	XXX	
035 617 05.	17	9	17	M 6	SW 5	7,6			XXX	
035 616 05.	19	9	16	M 6	SW 5	9,6		XXX	XXX	
035 620 05.	19	9	20	M 6	SW 5	10,4	XXX	XXX	XXX	
035 812 05.	17	10	11,5	M 8	SW 5	6,7	XXX	XXX	XXX	
035 817 15.	17	11	17	M 8	SW 5	6,5		XXX	XXX	
035 825 15.	17	11	25	M 8	SW 5	9,6		XXX	XXX	
035 816 05.	20	10	16	M 8	SW 5	8,8	XXX	XXX	XXX	
035 118 06.	22,5	13	18	M 10	SW 6	15,0	XXX		XXX	

↑ Please complete in order
¹⁾ 7 for steel brown coloured
²⁾ 3 for steel nickel plated
³⁾ 1 for steel zinc plated



Matching RAMPA Screws type KF